

# HARBACH ELECTRONICS/PETER W. DAHL AMATEUR TRANSFORMER DATABASE

## 4

4000 VAC @ 1.0A CCS N PLATE TRANSFORMER  
CORE) A-0518/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 4000 VAC @ 1.0A CCS  
DM) HT = 10.000 WT = 8.825 DT = 8.313 MD = 4.500 MW = 6.250 WEIGHT) 66 LBS

4000 VAC @ 3.0A CCS PLATE TRANSFORMER  
CORE) A-0540/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 4000 VAC @ 3.0A CCS  
DM) HT = 13.500 WT = 11.950 DT = 10.125 MD = 5.625 MW = 7.500 WEIGHT) 164 LBS

4000 VAC @ 500MA CCS PLATE TRANSFORMER  
CORE) A-480 C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 230 VAC 50/60 HZ 1 PH  
S1) 4000 VAC @ 500MA CCS  
DM) HT = 8.375 WT = 8.075 DT = 7.688 MD = 3.937 MW = 5.500 WEIGHT) 46 LBS

4000/2400 VAC @ 3.0A CCS PLATE TRANSFORMER  
CORE) A-0540/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-2400-4000 VAC @ 3.0A CCS  
DM) HT = 13.500 WT = 11.950 DT = 10.125 MD = 5.625 MW = 7.500 WEIGHT) 164 LBS

4000/3200 VAC @ 2.0A CCS N PLATE TRANSFORMER  
CORE) A-0530/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-3200-4000 VAC @ 2.0A CCS  
DM) HT = 12.875 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4000/3500/3000 VAC @ 1.5A CS PLATE TRANSFORMER  
CORE) A-555/C C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-3000-3500-4000 VAC @ 1.5A CCS  
DM) HT = 12.856 WT = 12.765 DT = 9.100 MD = 4.375 MW = 8.510 WEIGHT) 119 LBS

4000/3500/3000/2500V @ 3A CS PLATE TRANSFORMER  
CORE) A-540 C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-230-240 VAC 60 HZ 1 PH  
S1) 0-2500-3000-3500-4000 VAC @ 3.0A CCS  
DM) HT = 13.500 WT = 11.950 DT = 10.125 MD = 5.625 MW = 7.500 WEIGHT) 164 LBS

4200 VAC @ 1.5A CCS KL PLATE TRANSFORMER  
CORE) A-0530/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-230-240 VAC 60 HZ 1 PH  
S1) 4200 VAC @ 1.5A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4200 VAC @ 2.0A ICAS F PLATE TRANSFORMER  
CORE) A-0525/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 110/220 VAC 60 HZ 1 PH  
S1) 4200 VAC @ 2.0A ICAS  
DM) HT = 10.769 WT = 9.825 DT = 9.188 MD = 5.000 MW = 6.437 WEIGHT) 86 LBS

4200 VCT @ 0.6A CCS I PLATE TRANSFORMER  
CORE) A-0480/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 120/240 VAC 60 HZ 1 PH  
S1) 4200 VCT @ 0.6A CCS  
DM) HT = 8.375 WT = 8.075 DT = 7.688 MD = 3.937 MW = 5.500 WEIGHT) 46 LBS

4500 VAC @ 1.5A CCS PLATE TRANSFORMER  
CORE) A-530 C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-210-230-240 VAC 60 HZ 1 PH  
S1) 4500 VAC @ 1.5A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4500 VAC @ 2.0A CCS N PLATE TRANSFORMER  
CORE) A-530 C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 4500 VAC @ 2.0A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4500/4000/2600V @ 2.0A CCS N PLATE TRANSFORMER  
CORE) A-0530/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-2600-4000-4500 VAC @ 2.0A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4600/4000 VAC @ 1.5A ICAS K PLATE TRANSFORMER  
CORE) A-0518/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 230 VAC 60 HZ 1 PH  
S1) 0-4000-4600 VAC @ 1.5A ICAS  
DM) HT = 10.000 WT = 8.825 DT = 8.313 MD = 4.500 MW = 6.250 WEIGHT) 66 LBS

4600/4000 VAC @ 2.0A CCS N PLATE TRANSFORMER  
CORE) A-0530/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-4000-4600 VAC @ 2.0A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4800 VAC @ 2.0A CCS N PLATE TRANSFORMER  
CORE) A-0530/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 4800 VAC @ 2.0A CCS  
DM) HT = 12.375 WT = 10.700 DT = 9.813 MD = 5.625 MW = 6.500 WEIGHT) 127 LBS

4800/4000/3500/2500V @ 3A CS PLATE TRANSFORMER  
CORE) A-0540/ C-CORE STYLE #) 10 HIPERSIL C-CORE  
PR) 0-220-240 VAC 60 HZ 1 PH  
S1) 0-2500-3500-4000-4800 VAC @ 3.0A CCS  
DM) HT = 14.000 WT = 11.950 DT = 10.125 MD = 5.625 MW = 7.500 WEIGHT) 164 LBS