

HARBACH ELECTRONICS/PETER W. DAHL AMATEUR TRANSFORMER DATABASE

M

MOD TRANSFORMER 1200 WATT PP 304TL'S @ 12,000 OHMS P-P
CORE) A-550/C C-CORE STYLE #) 09 HIPERSIL C-CORE
PR) 2872 VCT @ 0.34A CCS (12,000 OHMS P-P)
S1) 1768 VAC @ 0.39A CCS (2500 VDC @ .55A)
DM) HT = 15.625 WT = 11.000 DT = 9.375 MD = 6.750 MW = 8.000 WEIGHT) 137 LBS

MOD TRANSFORMER 30 WATT SINGLE 807 @ 450 VDC @ 150MA DC THRU SEC
CORE) EI-175 X 1.75 29GZ MX6 STYLE #) 04 E-I LAMINATED CORE
PR) 16.4 VAC @ 2.0A CCS (8 OHMS)
S1) 318 VAC @ 0.106A CCS (3000 OHMS)
DM) HT = 6.000 WT = 4.375 DT = 3.955 MD = 2.875 MW = 3.500 WEIGHT) 12 LBS

MOD TRANSFORMER 300 WATT PP 4CX150A'S @ 17600 OHMS P-P
CORE) A-0518/ C-CORE STYLE #) 09 HIPERSIL C-CORE
PR) 2100 VCT @ 0.17A CCS (17,600 OHMS P-P)
S1) 1414 VAC @ 0.18A CCS (2000 VDC @ .25A)
DM) HT = 10.144 WT = 6.656 DT = 5.563 MD = 4.500 MW = 6.000 WEIGHT) 38 LBS

MOD TRANSFORMER 500 WATT PP 813'S TO SINGLE 813 @ 2000 VDC @ .25A
CORE) A-0525/ C-CORE STYLE #) 09 HIPERSIL C-CORE
PR) 1768 VCT @ 0.2A CCS (PP 813'S 16K PP)
S1) 1414 VAC @ 0.25A DC (2000 VDC @ 0.25A)
DM) HT = 10.669 WT = 7.469 DT = 6.063 MD = 5.000 MW = 5.750 WEIGHT) 49 LBS