

HARBACH ELECTRONICS/PETER W. DAHL AMATEUR TRANSFORMER DATABASE

E

EICO 720 DC CHOKE L16
CORE) EI-100 X 1 STYLE #) 01 E-I LAMINATED CORE
PR) 8.0 HY @ 150MA DC (600 WVDC)
DM) HT = 2.580 WT = 3.080 DT = 2.100 MD = 0.000 MW = 3.563 WEIGHT) 2 LBS

EICO 720 POWER XFMR 90 WATT CW TRANSMITTER POWER TRANSFORMER
CORE) EI-150 X 2" 29GA M6X STYLE #) 06 E-I LAMINATED CORE
PR) 117 VAC 60 HZ 1 PH
S1) 1400 VCT @ 170 MA CCS
S2) 5 VAC @ 2A CCS
S3) 6.3 VAC @ 3A CCS
DM) HT = 3.188 WT = 4.500 DT = 3.750 MD = 3.000 MW = 3.750 WEIGHT) 10 LBS

ELDICO MODEL 1000 FIL/BIAS W/O 866A FIL WINDING (NEED SS 866A'S)
CORE) EI-125 X 1.25 STYLE #) 05 E-I LAMINATED CORE
PR) 115 VAC 60 HZ 1 PH
S1) 6.3 VAC @ 6.5A CCS
S2) 250 VCT @ 0.1A CCS
DM) HT = 3.750 WT = 3.125 DT = 2.825 MD = 2.250 MW = 2.500 WEIGHT) 4 LBS